





IF9030 N-Channel JFET

Features

- InterFET <u>N0903L Geometry</u>
- Low Noise: 0.7 nV/VHz Typical
- High Gain: 150mS Typical
- Low Rds(on): 6.0 Ohms Typical
- RoHS Compliant
- SMT, TH, and Bare Die Package options.

Applications

• Low-Noise, High Gain Amplifiers

Description

The -20V InterFET IF9030 JFET is targeted for low noise high gain amplifier designs. The IF9030 has a cutoff voltage of less than 2.0V ideal for low voltage applications. The TO-52 package is hermetically sealed and suitable for military applications.

TO-52 Bottom View

Product Summary

	Parameters	IF9030 Min	Unit
BV _{GSS}	Gate to Source Breakdown Voltage	-20	V
I _{DSS}	Drain to Source Saturation Current	30	mA
V _{GS(off)}	Gate to Source Cutoff Voltage	-0.35	V
GFS	Forward Transconductance	80	mS

Ordering Information Custom Part and Binning Options Available

Part Number	Description	Case	Packaging
IF9030T52	Through-Hole	TO-52	Bulk
IF9030COT	Chip Orientated Tray (COT Waffle Pack)	COT	400/Waffle Pack
IF9030CFT	Chip Face-up Tray (CFT Waffle Pack)	CFT	400/Waffle Pack



Disclaimer: It is the Buyers responsibility for designing, validating and testing the end application under all field use cases and extreme use conditions. Guaranteeing the application meets required standards, regulatory compliance, and all safety and security requirements is the responsibility of the Buyer. These resources are subject to change without notice.







Electrical Characteristics

Maximum Ratings (@ T_A = 25°C, Unless otherwise specified)

	Parameters	Value	Unit
VRGS	Reverse Gate Source and Gate Drain Voltage	-20	V
I_{FG}	Continuous Forward Gate Current	10	mA
PD	Continuous Device Power Dissipation	300	mW
Р	Power Derating	2.4	mW/°C
Τı	Operating Junction Temperature	-55 to 125	°C
T _{STG}	Storage Temperature	-65 to 200	°C

Static Characteristics (@ TA = 25°C, Unless otherwise specified)

	Parameters	Conditions	Min	Тур	Max	Unit
V(BR)GSS	Gate to Source Breakdown Voltage	$V_{DS} = 0V, I_G = -1\mu A$	-20			V
I _{GSS}	Gate to Source Reverse Current	V_{GS} = -10V, V_{DS} = 0V			-0.1	nA
V _{GS(OFF)}	Gate to Source Cutoff Voltage	V _{DS} = 10V, I _D = 0.5nA	-0.35		-2.0	V
I _{DSS}	Drain to Source Saturation Current	$V_{GS} = 0V, V_{DS} = 10V$ (Pulsed)	30	100	300	mA

Dynamic Characteristics (@ TA = 25°C, Unless otherwise specified)

	Parameters	Conditions	Min	Тур	Max	Unit
Gfs	Forward Transconductance	V _{DS} = 10V, V _{GS} = 0V, f = 1kHz	80	150		mS
C _{iss}	Input Capacitance	V _{DS} = 10V, I _D = 5mA, f = 1MHz			60	pF
Crss	Reverse Transfer Capacitance	V _{DS} = 10V, I _D = 5mA, f = 1MHz			20	pF
en	Equivalent Circuit Input Noise Voltage	V _{DS} = 4V, I _D = 5mA, f = 1kHz		0.7		nV/√Hz






Order

Now

Typical IF9030 Characteristics








Order Now

Technical

Support

Typical IF9030 Characteristics (Continued)








Order

Now


IF9030

TO-52 Mechanical and Layout Data

Package Outline Data



Suggested Through-Hole Layout



- 1. All linear dimensions are in millimeters.
- 2. Package weight approximately 0.26 grams
- 3. Bulk product is shipped in standard ESD shipping material
- 4. Refer to JEDEC standards for additional information.

- 1. All linear dimensions are in millimeters.
- 2. The suggested land pattern dimensions have been provided as a straight lead reference only. A more robust pattern may be desired for wave soldering and/or bent lead configurations.